

DIGITAL CONDUCTIVITY METER

METZ – 602 M



SPECIFICATIONS

Display	3.5 Digit LED.
Range	5 Ranges, 0 to 1000 Mhos / cm. Auto Ranging.
Accuracy	$\pm 1\%$ FS ± 1
Temp. Compensation	Manual 0 to 50 deg.C
Cell Constant	Adjustable.
Sensor	Conductivity Cell.
Power	230V $\pm 10\%$ 50 Hz.